

10/009594

Attorney Docket: 951/50636
PATENTIN THE UNITED STATES PATENT AND TRADEMARK OFFICE9 / Sub. Spec. N.E.
E. Willis
10-29-02

Applicant: THOMAS SEIDENFUSS

Serial No.: TO BE ASSIGNED

PCT No.: PCT/EP00/09798

Filed: DECEMBER 11, 2001

Title: INPUT CIRCUIT FOR INDUCTIVE SPEED SENSOR

SUBMISSION OF SUBSTITUTE SPECIFICATION

Box PCT


December 11, 2001

Assistant Commissioner for Patents
Washington, D.C. 20231

Sir:

Attached is a Substitute Specification and a marked-up copy of the original specification. I certify that said substitute specification contains no new matter and includes the changes indicated in the marked-up copy of the original specification.

Respectfully submitted,

Gary R. Edwards
Registration No. 31,824
Song Zhu
Registration No. 44,420CROWELL & MORING, LLP
P.O. Box 14300
Washington, DC 20044-4300
Telephone No.: (202) 624-2500
Facsimile No.: (202) 628-8844
GRE:SZ:tlm
(CAM #: 80437.746)

OK to enter
DK 9/10/07

10009594.072202
JC07R PCT/PTO 11 DEC 2001
10/009594

i / PRTS

Clean Substitute Specification
Attorney Docket No. 951/50636

Input Circuit for Inductive Speed Sensor

BACKGROUND AND SUMMARY OF THE INVENTION

This application claims the priority of PCT International Application No. PCT/EP00/09798, filed 6 October 2000 and German patent document 199 54 115.9, filed November 11, 1999, the disclosure of which is expressly incorporated by reference herein.

The invention relates to an input circuit for a signal from an inductive speed sensor.

Many internal combustion engines use transmitter wheels with inductive sensors to determine, for example, the position of the crankshaft. Not only are inductive sensors of this type rugged and usable at very high temperatures, they are also extremely inexpensive. However, the amplitude of the signal depends on the speed, covering a range from a few millivolts to more than 100 volts. Electronic circuits are normally used in order to be able to detect low amplitudes at low speeds, on the one hand, while reaching, on the other hand, the highest possible level of noise immunity during normal engine operation, i.e. in the presence of high amplitudes. The electronic circuits either divide the existing sensor voltage in one or more stages, or they switch the switching thresholds of evaluating comparators over.

Clean Substitute Specification
Attorney Docket No. 951/50636

Both of these methods measure the average level of the sensor voltage and effect the switch-over of their evaluation dependent on the latter.

A disadvantage of this process is that it necessarily involves a relatively high level of complex circuitry in order to determine the average amplitude of the signal, to switch-over the thresholds or voltage dividers, to provide a hysteresis for the switch-over and to prevent undesirable additional edges that may occur in the more sensitive area during a switch-back. Therefore, specially designed and costly so-called ASICs are often used.

One object of the present invention is to provide an input circuit of the kind described at the outset that can be used to achieve a high degree of input sensitivity during the start-up phase and a good signal-to-noise ratio during normal engine operation utilizing the simplest means.

This and other objects and advantages are achieved by the input circuit according to the invention, in which a voltage divider for a signal amplitude is no longer switched over on the basis of an average sensor signal value but on the basis of the speed. A precise analysis of the above-mentioned problem

Clean Substitute Specification
Attorney Docket No. 951/50636

revealed that the low amplitudes occur, for the most part, only during the start-up process (that is, when the engine starter rotates at less than 100 rpm). But once the engine starts, the idling speed is reached within a very short time. Idling speeds, however, are within a range of approximately 500 to 1,000 rpm. At this speed, the amplitude of the transmitter signal reached approximately 10 times the initial amplitude. The amplitude, in turn, changes by a maximum factor of ten across the entire remaining speed range. The invention takes advantage of the dependence of the signal amplitude on speed.

Specifically, a micro-controller can provide the speed to the engine control, where this dimension is already present. The speed thresholds and the switching hysteresis are also easily adjustable with the present invention.

Furthermore, if taking into account that the initial sensitivity level is necessary only during the start-up phase, a simple switch-over threshold will be enough to ensure sufficient noise immunity during normal engine operation.

Other objects, advantages and novel features of the present invention will become apparent from the following detailed

Clean Substitute Specification
Attorney Docket No. 951/50636

description of the invention when considered in conjunction with the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

The single figure of the drawing depicts an input circuit according to the invention.

DETAILED DESCRIPTION OF THE DRAWINGS

Referring to the Figure, the input circuit according to the invention is comprised of two circuit inputs (or connector pins) 1, 2, to which an inductive transmitter (not shown) can be connected. The two circuit inputs 1 and 2 are loaded via a resistor R1.

The circuit input 2 is connected to a voltage divider, comprised of the resistors R2 and R3, with the resistor R2 connecting the circuit input 2 to the ground, and the resistor R3 being connected to a constant voltage of 5V. The reference level of the transmitter is raised by way of the voltage divider, which is comprised of the resistors R2 and R3; as a result, it is possible to detect negative amplitudes using a comparator K.

Clean Substitute Specification
Attorney Docket No. 951/50636

The circuit input 1 is connected to a first input (-) of the comparator K via a resistor R4. Two Zener-diodes D1 and D2, connected opposite in relation to each other, are arranged between the resistor R4 and the second circuit input 2; in conjunction with the resistor R4, they protect the comparator K from an input voltage that is too high.

The second input (+) of the comparator K is connected to the circuit input 2 via a resistor R6, and to the output of the comparator K via a resistor R7. The two resistors R6 and R7 define a switching hysteresis.

The output of the comparator K is connected to a micro-controller M (input E) which is used to evaluate the transmitter signal, and which in turn, uses this transmitter information to control the engine.

Another resistor R5 and two p-channel MOS (metal-oxide semiconductor) field-effect transistors T1 and T2 are connected between the resistor R4 and the circuit input 2. Consequently, the first input (-) of the comparator K is connected via the resistor R4 to the circuit input 1 and via the combination of the resistor R5 and the two MOS field-effect transistors T1 and T2 to the circuit input 2. Using the combination of the components

Clean Substitute Specification
Attorney Docket No. 951/50636

R4, R5, T1 and T2, it is possible to realize a switchable voltage divider and, therefore, a controllable amplitude reduction at the comparator K.

The two MOS field-effect transistors T1 and T2 are necessary because of the negative sensor voltages; and they are both arranged in series and aligned in different switching directions. The inputs of the two MOS field-effect transistors T1 and T2 are connected to an output A of the micro-controller M and controlled by the latter. In the present case, the inductive sensor supplies +/- 1.3 volts at approximately 100 rpm.

At 1,000 rpm it generates +/- 12.7 volts. The switching threshold of the comparator is at approximately +/- 1.2 volts.

If resistance values of 51.1 k Ω are used for R4 and of 11.5 k Ω for R5, the resulting switching thresholds are higher by a factor of 5 (or approximately +/- 6 volts). This threshold provides a good signal-to-noise ratio.

If a vehicle in which the device is installed is started up and current is supplied to the micro-controller M, latter initially switches the two MOS field-effect transistors T1 and T2 via its output pin A to a high-impedance state. Thus, the sensor signal originating from the inductive sensor or transmitter (not shown) is applied, undamped, at the comparator

Clean Substitute Specification
Attorney Docket No. 951/50636

K. High amplitudes, however, are limited by way of the two diodes D1 and D2.

The micro-controller M evaluates the digitized signal from the comparator K and emits a signal if the established speed threshold is exceeded. This causes the micro-controller M to switch the MOS field-effect transistors T1 and T2 to a low-impedance level, so that the sensor signal at the comparator K is reduced by the then-active voltage divider consisting of the resistors R4 and R5. The speed determination is now less sensitive with respect to noise in the sensor signal. The resistors - as mentioned above - are selected in such a way that the signal level at the comparator K is sufficient for safe switching even under the poorest conditions. It is beneficial if the change-over speed is below the no-load speed in order to prevent any back and forth switching while the engine is running.

The present invention ensures a high input sensitivity during the start-up phase and a good signal-to-noise ratio during engine operation using the simplest means. Significant cost savings are realized in comparison to a conventional solution that uses a so-called ASIC.

Clean Substitute Specification
Attorney Docket No. 951/50636

The foregoing disclosure has been set forth merely to illustrate the invention and is not intended to be limiting. Since modifications of the disclosed embodiments incorporating the spirit and substance of the invention may occur to persons skilled in the art, the invention should be construed to include everything within the scope of the appended claims and equivalents thereof.

1 / PRTS

Input Circuit for Inductive Speed Sensor

BACKGROUND AND SUMMARY OF THE INVENTION

This application claims the priority of PCT International Application No. PCT/EP00/09798, filed 6 October 2000 and German patent document 199 54 115.9, filed November 11, 1999, the disclosure of which is expressly incorporated by reference herein.

The invention relates to an input circuit for a signal from an inductive speed sensor. [according to the preamble of claim 1.]

Many internal combustion engines use transmitter wheels with inductive sensors to determine, for example, the position of the crankshaft. Not only are inductive sensors of this type [very] rugged and usable at very high temperatures, they are also extremely inexpensive. However, the amplitude of the signal depends on the speed, covering a range from a few millivolts to more than 100 volts. Electronic circuits are normally used in order to be able to detect low amplitudes at low speeds, on the one hand, while reaching, on the other hand, the highest possible level of noise immunity during normal engine operation, i.e. in the presence of high amplitudes. The electronic circuits either

Marked up Substitute Specification
Attorney Docket No. 951/50636

divide [down] the existing sensor voltage in one or more stages, or they switch the switching thresholds of evaluating comparators over. Both of [the above-named] these methods measure the average level of the sensor voltage and effect the switch-over of their evaluation dependent on the latter.

A disadvantage of [It is disadvantageous that] this process is that it necessarily involves a relatively high level of complex circuitry in order to determine the average amplitude of the signal, to switch-over the thresholds or voltage dividers, to provide a hysteresis for the switch-over and to prevent undesirable additional edges that may occur in the more sensitive area during a switch-back. Therefore, specially designed and costly so-called ASICs are often used.

One object [It is the subject-matter] of the present invention is to provide an input circuit of the kind described at the outset that can be used to achieve a high degree of input sensitivity during the start-up phase and a good signal-to-noise ratio during normal engine operation utilizing the simplest means.

This and other objects and advantages are achieved by the input circuit according to [This objective is achieved with the

Marked up Substitute Specification
Attorney Docket No. 951/50636

characteristics specified in claim 1. A key concept of] the invention, in which [provides that] a voltage divider [of] for a signal amplitude is no longer switched over on the basis of an average sensor signal value but on the basis of the speed. A precise analysis of the above-mentioned problem revealed that the low amplitudes occur, for the most part, only during the start-up process[, i.e.] (that is, when the engine starter rotates at less than 100 rpm). But once the engine starts, the idling speed is reached within a very short time. Idling speeds, however, are within a range of approximately 500 to 1,000 rpm. At this speed, the amplitude of the transmitter signal reached approximately 10 times the initial amplitude. The amplitude, in turn, changes [at] by a maximum factor [10] of ten across the entire remaining speed range. The invention takes advantage of the dependence of the signal amplitude on speed.

Specifically, a micro-controller can provide the speed to the engine control, where this dimension is already present. The speed thresholds and the switching hysteresis are also easily adjustable with the present invention.

Furthermore, if taking into account that the initial sensitivity level is necessary only [necessary] during the start-up phase, a simple switch-over threshold will be enough to ensure

Marked up Substitute Specification
Attorney Docket No. 951/50636

[a] sufficient noise immunity during normal engine operation.

Other objects, advantages and novel features of the present invention will become apparent from the following detailed description of the invention when considered in conjunction with the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

[Other characteristics are defined in the sub-claims.]

[In the following, the invention will be described in greater detail utilizing a special embodiment and in reference to the single attached drawing.]

DETAILED DESCRIPTION OF THE DRAWINGS

The single figure of the drawing depicts an input circuit according to the invention. [that]

Referring to the Figure, the input circuit according to the invention is comprised of two circuit inputs (or connector pins) 1, 2, to which an inductive transmitter (not shown [here]) can be connected. The two circuit inputs 1 and 2 are loaded via a resistor R1.

Marked up Substitute Specification
Attorney Docket No. 951/50636

[Moreover, the] The circuit input 2 is connected to a voltage divider, comprised of the resistors R2 and R3, [in such a way that] with the resistor R2 [connects] connecting the circuit input 2 to the ground, and the resistor R3 being connected [connects the circuit input 2] to a constant voltage of 5V. The reference level of the transmitter is raised by way of the voltage divider, which is comprised of the resistors R2 and R3; as a result, it is possible to detect negative amplitudes using a comparator K.

The circuit input 1 is connected to a first input (-) of the comparator K via a resistor R4. Two Zener-diodes D1 and D2, [wired] connected opposite in relation to each other, are arranged between the resistor R4 and the second circuit input 2; in conjunction with the resistor R4, they protect the comparator K from an input voltage that is too high.

The second input (+) of the comparator K is connected to the circuit input 2 via a resistor R6, and [. Also, the second input (+) of the comparator K is also connected] to the output of the comparator K via a resistor R7. The two resistors R6 and R7 define a switching hysteresis.

Marked up Substitute Specification
Attorney Docket No. 951/50636

The output of the comparator K is connected to a micro-controller M (input E) [that] which is used to evaluate the transmitter signal, and which [. The micro-controller M,] in turn, uses this transmitter information to control the engine.

Another resistor R5 and two p-channel MOS [[] (metal-oxide semiconductor) []] field-effect transistors T1 and T2 are [wired] connected between the resistor R4 and the circuit input 2. Consequently, the first input (-) of the comparator K is connected via the resistor R4 to the circuit input 1 and via the combination of the resistor R5 and the two MOS field-effect transistors T1 and T2 to the circuit input 2. Using the combination of the components R4, R5, T1 and T2, it is possible to realize a switchable voltage divider and, therefore, a controllable amplitude reduction at the comparator K.

The two MOS field-effect transistors T1 and T2 are necessary because of the negative sensor voltages; and they are both arranged in series and aligned in different switching directions. The inputs of the two MOS field-effect transistors T1 and T2 are connected to an output A of the micro-controller M and controlled by the latter. In the present case, the inductive sensor supplies +/- 1.3 volts at approximately 100 rpm. At 1,000 rpm it generates +/- 12.7 volts. The switching

Marked up Substitute Specification
Attorney Docket No. 951/50636

threshold of the comparator is at approximately +/- 1.2 volts.

If resistance values of 51.1 k Ω are used for R4 and of 11.5 k Ω for R5, the resulting switching thresholds are higher by a factor of 5[, i.e.] (or approximately +/- 6 volts). This threshold provides a good signal-to-noise ratio.

If [the] a vehicle in which the device is installed is started up and current is supplied to the micro-controller M, [the micro-controller M] latter initially switches the two MOS field-effect transistors T1 and T2 via its output pin A to a high-impedance state. Thus, the sensor signal originating from the [(not shown)] inductive sensor or transmitter (not shown) is applied, undamped, at the comparator K. High amplitudes, however, are limited by way of the two diodes D1 and D2.

The micro-controller M evaluates the digitized signal [coming] from the comparator K and emits a signal if the established speed threshold is exceeded. This causes the micro-controller M to switch the MOS field-effect transistors T1 and T2 to a low-impedance level, so that [allowing for] the sensor signal at the comparator K [to be] is reduced by the then-active voltage divider consisting of the resistors R4 and R5. The speed determination is now less sensitive with respect to noise in the sensor signal. The resistors - as mentioned above - are selected

Marked up Substitute Specification
Attorney Docket No. 951/50636

in such a way that the signal level at the comparator K is sufficient for safe switching even under the poorest conditions.

It is beneficial if the change-over speed is below the no-load speed in order to prevent any back and forth switching while the engine is running.

The present invention ensures a high input sensitivity during the start-up phase and a good signal-to-noise ratio during engine operation using the simplest means. Significant cost savings are realized in comparison to a conventional solution that uses a so-called ASIC.

The foregoing disclosure has been set forth merely to illustrate the invention and is not intended to be limiting. Since modifications of the disclosed embodiments incorporating the spirit and substance of the invention may occur to persons skilled in the art, the invention should be construed to include everything within the scope of the appended claims and equivalents thereof.